

FAN7317

LCD Backlight Inverter Drive IC

Features

- High-Efficiency Single-Stage Power Conversion
- Wide Input Voltage Range: 6V to 24V
- Backlight Lamp Ballast and Soft Dimming
- Minimal Required External Components
- Precision Voltage Reference Trimmed to 2%
- ZVS Full-Bridge Topology
- Soft-Start
- PWM Control at Fixed Frequency
- Burst Dimming Function
- Programmable Striking Frequency
- Open-Lamp Protection
- Open-Lamp Regulation
- Arc Protection
- Short-Lamp Protection
- CMP-High Protection
- High-FB Protection
- Thermal Shutdown
- 20-Pin SOIC

Applications

- LCD TV
- LCD Monitor

Description

The FAN7317 is a LCD backlight inverter drive IC that controls P-N full-bridge topology by using the new proprietary phase-shift method.

The FAN7317 provides a low-cost solution and reduces external components by integrating full wave rectifiers for open-lamp protection and regulation. The operating voltage range of the FAN7317 is wide, so an external regulator isn't necessary to supply the voltage to the IC.

The FAN7317 provides various protections, such as open-lamp regulation, open-lamp protection, arc protection, short-lamp protection, CMP-high protection, and FB-high protection, to increase the system reliability. The FAN7317 provides burst dimming function and analog dimming is possible, in a narrow range, by adding some external components.

The FAN7317 is available in a 20-SOIC package.

20-SOIC



Ordering Information

| Part Number | Package | Operating Temperature | Packing Method |
|-------------|---------|-----------------------|----------------|
| FAN7317M | 20-SOIC | -25 to +85°C | RAIL |
| FAN7317MX | 20-SOIC | -25 to +85°C | TAPE & REEL |

 All packages are lead free per JEDEC: J-STD-020B standard.

Block Diagram





Figure 1. Internal Block Diagram

Pin Configuration



F : Fairchild logo
P : Assembly site code
XY : Year & weekly code
TT : Die run code
FAN7317 : Device name

Figure 2. Package Diagram

Pin Definitions

| Pin # | Name | Description |
|-------|------|--|
| 1 | REF | This pin is 5V reference output. Typically, resistors are connected to this pin from CT pin and BCT pin. |
| 2 | BDIM | This pin is the input for burst dimming. The voltage range of 0.5 to 2V at this pin controls burst mode duty cycle from 0% to 100%. |
| 3 | BCT | This pin is for programming the frequency of the burst dimming. Typically, a capacitor is connected to this pin from ground and a resistor is connected to this pin from the REF pin. |
| 4 | OLP1 | This pin is for open-lamp protection and feedback control of lamp currents. It has the same functions as other OLP pins and is connected to the full-wave rectifier internally. In striking mode, if the minimum of rectified OLP inputs is less than 1V for 1.6s; or in normal mode, if the minimum of rectified OLP inputs is less than 0.5V for 10ms; the IC shuts down to protect the system in open lamp condition. The maximum of rectified OLP inputs is inputted to the negative of the error amplifier for feedback control of lamp current. |
| 5 | OLR1 | This pin is for open-lamp regulation. It has the same functions as other OLR pins and is connected to the full-wave rectifier internally. When the maximum of rectified OLR inputs is between 1.8V and 2V, the error amplifier output current is limited to 1 μ A; and when the maximum of rectified OLR inputs reaches 2V, the error amplifier output current is 0A and its output voltage maintains constant. The maximum of rectified OLR inputs is inputted to the negative of another error amplifier for feedback control of lamp voltage. When the maximum of rectified OLR inputs is more than 2.2V, another error amplifier for OLR is operating and lamp voltage is regulated. |
| 6 | OLP2 | This pin is for open-lamp protection and feedback control of lamp currents. Its functions are the same as the OLP1 pin. |
| 7 | OLR2 | This pin is for open-lamp regulation. Its functions are the same as the OLR1 pin. |
| 8 | GND | This pin is the ground. |
| 9 | OUTB | This pin is NMOS gate-drive output. |
| 10 | OUTA | This pin is PMOS gate-drive output. |
| 11 | OUTC | This pin is PMOS gate-drive output. |
| 12 | OUTD | This pin is NMOS gate-drive output. |
| 13 | VIN | This pin is the supply voltage of the IC. |
| 14 | OLR3 | This pin is for open-lamp regulation. Its functions are the same as the OLR1 pin. |
| 15 | OLP3 | This pin is for open-lamp protection and feedback control of lamp currents. Its functions are the same as the OLP1 pin. |
| 16 | OLR4 | This pin is for open-lamp regulation. Its functions are the same as the OLR1 pin. |
| 17 | OLP4 | This pin is for open-lamp protection and feedback control of lamp currents. Its functions are the same as the OLP1 pin. |
| 18 | ENA | This pin is for turning on/off the IC. |
| 19 | CMP | Error amplifier output. Typically, a compensation capacitor is connected to this pin from the ground. |
| 20 | CT | This pin is for programming the switching frequency. Typically, a capacitor is connected to this pin from ground and a resistor is connected to this pin from the REF pin. |

Absolute Maximum Ratings

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only.

| Symbol | Parameter | Min. | Max. | Unit |
|---------------|--|------|------|------|
| V_{IN} | IC Supply Voltage | 6 | 24 | V |
| T_A | Operating Temperature Range | -25 | +85 | °C |
| T_J | Operating Junction Temperature | | +150 | °C |
| T_{STG} | Storage Temperature Range | -65 | +150 | °C |
| θ_{JA} | Thermal Resistance Junction-Air ^(1,2) | | 90 | °C/W |
| P_D | Power Dissipation | | 1.4 | W |

Notes:

1. Thermal resistance test board. Size: 76.2mm x 114.3mm x 1.6mm (1S0P); JEDEC standard: JESD51-2, JESD51-3.
2. Assume no ambient airflow.

Pin Breakdown Voltage

| Pin # | Name | Value | Unit | Pin # | Name | Value | Unit |
|-------|------|-------|------|-------|------|-------|------|
| 1 | REF | 7 | V | 11 | OUTC | 24 | V |
| 2 | BDIM | 7 | | 12 | OUTD | 7 | |
| 3 | BCT | 7 | | 13 | VIN | 24 | |
| 4 | OLP1 | ±7 | | 14 | OLR3 | ±7 | |
| 5 | OLR1 | ±7 | | 15 | OLP3 | ±7 | |
| 6 | OLP2 | ±7 | | 16 | OLR4 | ±7 | |
| 7 | OLR2 | ±7 | | 17 | OLP4 | ±7 | |
| 8 | GND | 7 | | 18 | ENA | 7 | |
| 9 | OUTB | 7 | | 19 | CMP | 7 | |
| 10 | OUTA | 24 | | 20 | CT | 7 | |

Electrical Characteristics

For typical values, $T_A = 25^\circ\text{C}$, $V_{IN} = 15\text{V}$, and $-25^\circ\text{C} \leq T_A \leq 85^\circ\text{C}$, unless otherwise specified. Specifications to $-25^\circ\text{C} \sim 85^\circ\text{C}$ are guaranteed by design based on final characterization results.

| Symbol | Parameter | Test Conditions | Min. | Typ. | Max. | Unit |
|--|---------------------------------------|--|------|------|-------|------------------|
| Under-Voltage Lockout Section (UVLO) | | | | | | |
| V_{th} | Start Threshold Voltage | | 4.9 | 5.2 | 5.5 | V |
| V_{thys} | Start Threshold Voltage Hysteresis | | 0.20 | 0.45 | 0.60 | V |
| I_{st} | Start-up Current | $V_{IN} = 4.5\text{V}$ | | 70 | 100 | μA |
| I_{op} | Operating Supply Current | $V_{IN} = 15\text{V}$, Not switching | | 2.0 | 3.5 | mA |
| ON/OFF Section | | | | | | |
| V_{on} | On State Input Voltage | | 2 | | 5 | V |
| V_{off} | Off Stage Input Voltage | | | | 0.7 | V |
| I_{sb} | Stand-by Current | $V_{IN} = 15\text{V}$, ENA = Low | | 120 | 170 | μA |
| R_{ENA} | Pull-down Resistor | | 130 | 200 | 270 | $\text{k}\Omega$ |
| Reference Section (Recommend $1\mu\text{F}$ X7R Capacitor) | | | | | | |
| V_5 | 5V Regulation Voltage | $0 \leq I_5 \leq 3\text{mA}$ | 4.9 | 5.0 | 5.1 | V |
| V_{5line} | 5V Line Regulation | $6 \ll V_{IN} \ll 24\text{V}$ | | | 50 | mV |
| V_{5load} | 5V Load Regulation | $I_5 = 3\text{mA}$ | | | 50 | mV |
| Oscillator Section (Main) | | | | | | |
| f_{osc} | Oscillation Frequency | $T_A = 25^\circ\text{C}$, $CT = 220\text{pF}$, $RT = 100\text{k}\Omega$ | 93.9 | 97.0 | 100.5 | kHz |
| | | $CT = 220\text{pF}$, $RT = 100\text{k}\Omega$ | 93 | 97 | 101 | |
| f_{str} | Oscillator Frequency in Striking Mode | $T_A = 25^\circ\text{C}$, $CT = 220\text{pF}$, $RT = 100\text{k}\Omega$ | 120 | 124 | 129 | kHz |
| | | $CT = 220\text{pF}$, $RT = 100\text{k}\Omega$ | 119 | 124 | 129 | |
| I_{ctdcs} | CT Discharge Current | Striking | 0.99 | 1.14 | 1.29 | mA |
| I_{ctdc} | | Normal | 740 | 840 | 940 | μA |
| I_{ctcs} | CT Charge Current | Striking | -15 | -12 | -9 | μA |
| V_{cth} | CT High Voltage | | | 2 | | V |
| V_{ctl} | CT Low Voltage | | | 0.4 | | V |
| Oscillator Section (Burst) | | | | | | |
| f_{oscb} | Burst Oscillation Frequency | $T_A = 25^\circ\text{C}$, $BCT = 4.7\text{nF}$, $BRT = 1.4\text{M}\Omega$ | 303 | 314 | 326 | Hz |
| | | $BCT = 4.7\text{nF}$, $BRT = 1.4\text{M}\Omega$ | 302 | 314 | 326 | |
| I_{bctdc} | BCT Discharge Current | | 14 | 26 | 38 | μA |
| V_{bcth} | BCT High Voltage | | | 2 | | V |
| V_{bctl} | BCT Low Voltage | | | 0.5 | | V |

Electrical Characteristics (Continued)

For typical values, $T_A = 25^\circ\text{C}$, $V_{IN} = 15\text{V}$, and $-25^\circ\text{C} \leq T_A \leq 85^\circ\text{C}$, unless otherwise specified. Specifications to $-25^\circ\text{C} \sim 85^\circ\text{C}$ are guaranteed by design based on final characterization results.

| Symbol | Parameter | Test Conditions | Min. | Typ. | Max. | Unit |
|-------------------------------------|---|--|-------|-------|-------|-----------------|
| Error Amplifier Section | | | | | | |
| A_V | Open-loop Gain ⁽³⁾ | | | 37 | | dB |
| G_m | Error Amplifier Trans-conductance | | 20 | 40 | 60 | μmho |
| I_{sin} | Output Sink Current | OLP = 2.25V | -50 | -35 | -20 | μA |
| I_{sur} | Output Source Current | OLP = 0.8V | 12 | 22 | 32 | μA |
| I_{bsin} | Burst CMP Sink Current | | 38 | 52 | 66 | μA |
| V_{135p} | 1.35V Regulation Voltage | $T_A = 25^\circ\text{C}$ | 1.275 | 1.350 | 1.421 | V |
| | | | 1.255 | 1.350 | 1.444 | |
| I_{olpi} | OLP Input Current | OLP = 2V | -1 | 0 | 1 | μA |
| I_{olpo} | OLP Output Current | OLP = -2V | -30 | -20 | -10 | μA |
| V_{olpr} | OLP Input Voltage Range ⁽³⁾ | | -4 | | 4 | V |
| Open-Lamp Regulation Section | | | | | | |
| I_{olr1} | Error Amplifier Source Current for Open-Lamp Regulation | Striking, OLR = $V_{\text{olr1}} + 0.05$ | -2.0 | -1.0 | -0.1 | μA |
| I_{olr2} | | OLR = 2.1V | | 0 | | μA |
| V_{olr1} | Open-Lamp Regulation Voltage 1 | Striking | 1.65 | 1.80 | 1.95 | V |
| V_{olr2} | Open-Lamp Regulation Voltage 2 | Striking | 1.95 | 2.05 | 2.15 | V |
| V_{olr3} | Open-Lamp Regulation Voltage 3 | | 2.1 | 2.2 | 2.3 | V |
| G_{mOLR} | OLR Error Amplifier Trans-conductance | | 200 | 350 | 500 | μmho |
| I_{olrsi} | OLR Error Amplifier Sink Current | Normal, OLR = 2.5V | 50 | 70 | 90 | μA |
| I_{olri} | OLR Input Current | OLR = 1.5V | 10 | 17 | 24 | μA |
| I_{olro} | OLR Output Current | OLR = -1.5V | -25 | -15 | -7 | μA |
| V_{olrr} | OLR Input Voltage Range ⁽³⁾ | | -4 | | 4 | V |

Note:

3. These parameters, although guaranteed, are not 100% tested in production.

Electrical Characteristics (Continued)

For typical values, $T_A = 25^\circ\text{C}$, $V_{IN} = 15\text{V}$, and $-25^\circ\text{C} \leq T_A \leq 85^\circ\text{C}$, unless otherwise specified. Specifications to $-25^\circ\text{C} \sim 85^\circ\text{C}$ are guaranteed by design based on final characterization results.

| Protection Section | | | | | | |
|---------------------------|--|---|--------------|------------|--------------|------------------|
| V_{olp0} | Open-Lamp Protection Voltage 0 ⁽⁴⁾ | Open Lamp in Striking | 0.95 | 1.00 | 1.05 | V |
| V_{olp1} | Open-Lamp Protection Voltage 1 | Open Lamp | 0.44 | 0.51 | 0.58 | V |
| V_{cmpr} | CMP-High Protection Voltage | | 2.95 | 3.05 | 3.15 | V |
| V_{arcp} | Arc Protection Voltage | | 2.90 | 3.05 | 3.20 | V |
| V_{hfbp} | High-FB Protection Voltage ⁽⁴⁾ | | 3.4 | 3.5 | 3.6 | V |
| V_{slp} | Short Lamp Protection Voltage | | 0.24 | 0.32 | 0.40 | V |
| T_{olps} | Open-Lamp Protection Delay ⁽⁴⁾ | Striking, $f_{osc} = 330\text{Hz}$ | | 1.6 | | s |
| T_{olpn} | | Normal, $f_{osc} = 100\text{kHz}$ | | 10 | | ms |
| T_{cmprs} | High-CMP Protection Delay ⁽⁴⁾ | Striking, $f_{osc} = 330\text{Hz}$ | | 1.6 | | s |
| T_{cmprn} | | Normal, $f_{osc} = 100\text{kHz}$ | | 10 | | ms |
| T_{olr} | Open-Lamp Regulation Delay ⁽⁴⁾ | Normal, $f_{osc} = 100\text{kHz}$ | | 320 | | μs |
| T_{slp} | Short Lamp Protection Delay ⁽⁴⁾ | Normal, $f_{osc} = 100\text{kHz}$ | | 1 | | ms |
| TSD | Thermal Shutdown ⁽⁴⁾ | | | 150 | | $^\circ\text{C}$ |
| Output Section | | | | | | |
| V_{pdhv} | PMOS Gate High Voltage ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | V_{IN} | | V |
| V_{phlv} | PMOS Gate Low Voltage | $V_{IN} = 15\text{V}$ | $V_{IN}-6.5$ | $V_{IN}-7$ | $V_{IN}-7.5$ | V |
| V_{ndhv} | NMOS Gate High Voltage | $V_{IN} = 15\text{V}$ | 6.5 | 7.0 | 7.5 | V |
| V_{ndlv} | NMOS Gate Low Voltage ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | 0 | | V |
| V_{puv} | PMOS Gate Voltage with UVLO Activated | $V_{IN} = 4.5\text{V}$ | $V_{IN}-0.3$ | | | V |
| V_{nuv} | NMOS Gate Voltage with UVLO Activated | $V_{IN} = 4.5\text{V}$ | | | 0.3 | V |
| I_{pdsur} | PMOS Gate Drive Source Current ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | -200 | | mA |
| I_{pdsin} | PMOS Gate Drive Sink Current ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | 300 | | mA |
| I_{ndsur} | NMOS Gate Drive Source Current ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | 200 | | mA |
| I_{ndsln} | NMOS Gate Drive Sink Current ⁽⁴⁾ | $V_{IN} = 15\text{V}$ | | -300 | | mA |
| t_r | Rising Time ⁽⁴⁾ | $V_{IN} = 15\text{V}$, $C_{load} = 2\text{nF}$ | | 70 | | ns |
| t_f | Falling Time ⁽⁴⁾ | $V_{IN} = 15\text{V}$, $C_{load} = 2\text{nF}$ | | 70 | | ns |
| Maximum / Minimum Overlap | | | | | | |
| | Minimum Overlap Between Diagonal Switches ⁽⁴⁾ | $f_{osc} = 100\text{kHz}$ | | 0 | | % |
| | Maximum Overlap Between Diagonal Switches ⁽⁴⁾ | $f_{osc} = 100\text{kHz}$ | 86 | | 90 | % |
| Dead Time | | | | | | |
| | PDR_A/NDR_B ⁽⁴⁾ | | 150 | 200 | 250 | ns |
| | PDR_C/NDR_D ⁽⁴⁾ | | 150 | 200 | 250 | ns |

Note:

4. These Parameters, although guaranteed, are not 100% tested in production.

Typical Performance Characteristics




Figure 3. Start Threshold Voltage vs. Temp.




Figure 4. Start Threshold Voltage Hys. vs. Temp.




Figure 5. Start-up Current vs. Temp.




Figure 6. Operating Current vs. Temp.




Figure 7. Standby Current vs. Temp.




Figure 8. Pull-down Resistor vs. Temp.

Typical Performance Characteristics (Continued)




Figure 9. 5V Regulation Voltage vs. Temp.




Figure 10. Oscillation Frequency vs. Temp.




Figure 11. Oscillation Frequency in Striking vs. Temp.




Figure 12. CT Discharge Current in Striking vs. Temp.




Figure 13. CT Discharge Current vs. Temp.




Figure 14. CT Charge Current vs. Temp.

Typical Performance Characteristics (Continued)




Figure 15. CT High Voltage vs. Temp.




Figure 16. CT Low Voltage vs. Temp.




Figure 17. Burst Dimming Frequency vs. Temp.




Figure 18. BCT Discharge Current vs. Temp.




Figure 19. BCT High Voltage vs. Temp.




Figure 20. BCT Low Voltage vs. Temp.

Typical Performance Characteristics (Continued)




Figure 21. Error Amp. GM vs. Temp.




Figure 22. Error Amp. Sink Current vs. Temp.




Figure 23. Error Amp. Source Current vs. Temp.




Figure 24. Burst CMP Sink Current vs. Temp.




Figure 25. 1.35V Regulation Voltage vs. Temp.




Figure 26. OLP Input Current vs. Temp.

Typical Performance Characteristics (Continued)




Figure 27. OLP Output Current vs. Temp.




Figure 28. Error Amp. Source Current 1 vs. Temp.




Figure 29. Error Amp. Source Current 2 vs. Temp.




Figure 30. OLR Error Amp. GM vs. Temp.




Figure 31. OLR Error Amp. Sink Current vs. Temp.




Figure 32. OLR Input Current vs. Temp.

Typical Performance Characteristics (Continued)




Figure 33. OLR Output Current vs. Temp.




Figure 34. Open-Lamp Protection Voltage1 vs. Temp.




Figure 35. High-CMP Protection Voltage vs. Temp.




Figure 36. Arc Protection Voltage vs. Temp.




Figure 37. Short Lamp Protection Voltage vs. Temp.




Figure 38. PMOS Gate Low Voltage vs. Temp.

Functional Description

UVLO: The under-voltage lockout (UVLO) circuit guarantees the stable operation of the IC's control circuit by stopping and starting it as a function of the V_{IN} value. The UVLO circuit turns on the control circuit when V_{IN} exceeds 5.2V. When V_{IN} is lower than 4.75V, the IC start-up current is less than 100 μ A.

ENA: Applying voltage higher than 2V to the ENA pin enables the IC. Applying voltage lower than 0.7V to the ENA pin disables the IC.

Main Oscillator: In normal mode, the external timing capacitor (CT) is charged by the current flowing from the reference voltage source, which is formed by the timing resistor (RT) and the timing capacitor (CT). The sawtooth waveform charges up to 2V. Once CT voltage reaches 2V, the CT starts discharging down to 0.4V. Next, the CT starts charging again and a new switching cycle begins, as shown in Figure 39. The main frequency is programmed by adjusting the RT and CT value. The main frequency is calculated as:

$$f_{osc} = \frac{1}{RT \cdot CT \cdot \ln\left(\frac{3.864 \cdot RT - 13800}{2.52 \cdot RT - 13800}\right)} \text{ [Hz]} \quad (1)$$




Figure 39. Main Oscillator Circuit

In striking mode, the external timing capacitor (CT) is charged by the current flowing from the reference voltage source and 12 μ A current source, which increases the frequency. If the product of RT and CT value is constant, the striking frequency is depending on CT and is calculated as:

$$f_{str} = \frac{1}{RT \cdot CT \cdot \ln\left(\frac{13.8 + (3I_1 - 4.6I_2)RT}{13.8 + (4.6I_1 - 3I_2)RT}\right)} \text{ [Hz]} \quad (2)$$

$$\therefore I_1 = 12 \times 10^{-6} \text{ A}, I_2 = 1.128 \times 10^{-3} \text{ A}$$

Burst Dimming Oscillator: The burst dimming timing capacitor (BCT) is charged by the current flowing from the reference voltage source, which is formed by the burst dimming timing resistor (BRT) and the burst dimming timing capacitor (BCT). The sawtooth waveform charges up to 2V. Once the BCT voltage reaches 2V, the capacitor begins discharging down to 0.5V. Next, the BCT starts charging again and a new burst dimming cycle begins, as shown in Figure 40. The burst dimming frequency is programmed by adjusting the BCT and BRT values. The burst dimming frequency is calculated as:

$$f_{OSCB} = \frac{1}{BRT \cdot BCT \cdot \ln\left(\frac{0.039 \cdot BRT - 4500}{0.026 \cdot BRT - 4500}\right)} \text{ [Hz]} \quad (3)$$

To avoid visible flicker, the burst dimming frequency should be greater than 120Hz.




Figure 40. Burst Dimming Oscillator Circuit

Analog Dimming: For analog dimming, the lamp intensity is controlled with the external dimming signal (V_{ADIM}) and resistors. Figure 41 shows how to implement an analog dimming circuit. The polarity of OLP1 should be reversed with respect to OLP2.




Figure 41. Analog Implementation Circuit

In full brightness, the maximum rms value of the lamp current is calculated as:

$$i_{rms}^{max} = 1.35 \frac{\pi}{2\sqrt{2}R_{S1}} [A] \quad (4)$$

The lamp intensity is inversely proportional to V_{ADIM} . As V_{ADIM} increases, the lamp intensity decreases and the rms value of the lamp current is calculated as:

$$i_{rms} = i_{rms}^{max} - \frac{\pi}{2\sqrt{2}} \frac{R_1}{R_{S2}R_2} V_{ADIM} [A] \quad (5)$$

$$\therefore R_{S2} = \frac{R_1 + R_2}{R_2} R_{S1} [\Omega]$$

Figure 42 shows the lamp current waveform vs. V_{ADIM} in an analog dimming mode.




Figure 42. Analog Dimming Waveforms

Burst Dimming: Lamp intensity is controlled with the BDIM signal over a wide range. When BDIM voltage is lower than BCT voltage, the lamp current is turned on; so, 0V on BDIM commands full brightness. The duty cycle of the PWM pulse determines the lamp brightness. The lamp intensity is inversely proportional to BDIM voltage. As BDIM voltage increases, the lamp intensity decreases. Figure 43 shows the lamp current waveform vs. DIM in negative analog dimming mode.




Figure 43. Burst Dimming Waveforms

Burst dimming can be implemented not only DC voltage, but also using PWM pulse as the BDIM signal. Figure 44 shows how to implement burst dimming using PWM pulse as BDIM signal.




Figure 44. Burst Dimming Using an External Pulse

During striking mode, burst dimming operation is disabled to guarantee continuous striking time. Figure 45 shows burst dimming is disabled during striking mode.




Figure 45. Burst Dimming During Striking Mode

Output Drives: FAN7317 uses the new phase-shift method for full-bridge Cold Cathode Fluorescent Lighting (CCFL) drive. As a result, the temperature difference between the left and the right leg is almost zero, because ZVS occurs in both of the legs by turns. The detail timing is shown in Figure 46.




Figure 46. MOSFETs Gate Drive Signal

Protections: The FAN7317 provides the following latch-mode protections: Open-Lamp Regulation (OLR), Arc Protection, Open-Lamp Protection (OLP), Short-Lamp Protection (SLP), CMP-High Protection, and Thermal Shutdown (TSD). The latch is reset when V_{IN} falls to the UVLO voltage or ENA is pulled down to GND.

Open-Lamp Regulation: When the maximum of the rectified OLR input voltages (V_{OLR}^{max}) is more than 2V, the IC enters regulation mode and controls CMP voltage. The IC limits the lamp voltage by decreasing CMP source current. If V_{OLR}^{max} is between 1.8V and 2V, CMP source current decreases from 22 μ A to 1 μ A. Then, if V_{OLR}^{max} reaches 2V, CMP source current decreases to 0 μ A, so CMP voltage remains constant and the lamp voltage also remains constant, as shown in Figure 47. Finally, if V_{OLR}^{max} is more than 2.2V, the error amplifier for OLR is operating and CMP sink current increases, so CMP voltage decreases and the lamp voltage maintains the determined value.

At the same time, while V_{OLR}^{max} is more than 2V, the counter starts counting 32 rectified OLR pulses in normal mode, then the IC enters shutdown, as shown in Figure 49. This counter is reset by detecting the positive edge of BCT. This protection is disabled in striking mode to ignite lamps reliably.




Figure 47. Open-Lamp Regulation in Striking Mode




Figure 48. Open-Lamp Regulation in Normal Mode




Figure 49. Over-Voltage Protection in Normal Mode

Arc Protection: If the maximum of the rectified OLR input voltages (V_{OLR}^{max}) is higher than 3V, the IC enters shutdown mode without delay, as shown in Figure 50.




Figure 50. Arc Protection

Open-Lamp Protection: If the minimum of the rectified OLP voltages (V_{OLP}^{min}) is less than 1V during initial operation, the IC operates in striking mode only for 1.6s, as shown in Figure 51. After ignition, if V_{OLP}^{min} is less than 0.5V in normal mode, the IC is shut down after a delay of 10ms, as shown in Figure 52.




Figure 51. Open-Lamp Protection in Striking Mode




Figure 52. Open-Lamp Protection in Normal Mode

Short-Lamp Protection: If the minimum of the rectified OLR voltages (V_{OLR}^{min}) is less than 0.3V in normal mode, the IC is shut down after a delay of 1ms, as shown in Figure 53. This protection is disabled in striking mode to ignite lamps reliably.




Figure 53. Short-Lamp Protection

CMP-High Protection: If CMP is more than 3V in normal mode, the IC is shut down after a delay of 10ms, as shown in Figure 54. This protection is disabled in striking mode to ignite lamps reliably.




Figure 54. CMP-High Protection

High-FB Protection: If the minimum of the rectified OLP voltages(V_{OLP}^{max}) is more than 3.5V, the counter starts counting eight rectified OLP pulses in normal mode, then the IC enters shutdown, as shown in Figure 55. This counter is reset by detecting the positive edge of BCT. This protection is disabled in striking mode to ignite lamps reliably.




Figure 55. High-FB Protection

Thermal Shutdown: The IC provides the function to detect the abnormal over-temperature. If the IC temperature exceeds approximately 150°C, the thermal shutdown triggers.

Typical Application Circuit (LCD Backlight Inverter)

| Application | Device | Input Voltage Range | Number of lamps |
|---------------------|---------|---------------------|-----------------|
| 22-Inch LCD Monitor | FAN7317 | 13±10% | 4 |

1. Features

- High-Efficiency Single-Stage Power Conversion
- P-N Full-Bridge Topology
- Reduces Required External Components
- Enhanced System Reliability through Protection Functions




Figure 56. Typical Application Circuit

2. Transformer Schematic Diagram




Figure 57. Transformer Schematic Diagram

3. Core & Bobbin

- Core: EFD2126
- Material: PL7
- Bobbin: EFD2126

4. Winding Specification

| Pin No. | Wire | Turns | Inductance | Leakage Inductance | Remarks |
|---------|-------------|-----------------------|------------|--------------------|----------|
| 5 → 2 | 1 UEW 0.4φ | 17 | 250μH | 16μH | 1kHz, 1V |
| 7 → 9 | 1 UEW 0.04φ | 2256(= 0+0+376•6) | 4.2H | 290mH | 1kHz, 1V |

5. BOM of the Application Circuit

| Part Ref. | Value | Description | Part Ref. | Value | Description |
|------------------------|--------|-------------|-------------------------------|-------------|-------------------------|
| Fuse | | | C14 | 3.3n | 50V 1608 K |
| F1 | 24V 3A | FUSE | C15 | 100n | 50V 1608 K |
| Resistor (SMD) | | | C17 | 1μ | 50V 2012 K |
| R1 | 10k | 1608 J | C18 | 4.7n | 50V 1608 K |
| R2 | 10k | 1608 J | C19 | 3.3n | 50V 1608 K |
| R3 | 200 | 1608 F | C21 | 3.3n | 50V 1608 K |
| R5 | 100k | 1608 F | Capacitor (DIP) | | |
| R6 | 10k | 1608 J | C4 | 3p | 3KV |
| R7 | 200 | 1608 F | C13 | 3p | 3KV |
| R8 | 75k | 1608 J | C16 | 3p | 3KV |
| R9 | 10k | 1608 J | C20 | 3p | 3KV |
| R10 | 8.2k | 1608 J | Electrolytic capacitor | | |
| R12 | 10k | 1608 J | C1 | 220μ | 25V |
| R13 | 200 | 1608 F | C2 | 220μ | 25V |
| R14 | 1.5M | 1608 F | MOSFET (SMD) | | |
| R15 | 10k | 1608 J | M1 | FDD8424H | Fairchild Semiconductor |
| R16 | 200 | 1608 F | M2 | FDD8424H | Fairchild Semiconductor |
| Capacitor (SMD) | | | Wafer (SMD) | | |
| C3 | 1μ | 50V 2012 K | CN1 | 12505WR-10 | |
| C5 | 1μ | 50V 2012 K | CN2 | 35001WR-02A | |
| C6 | 3.3n | 50V 1608 K | CN3 | 35001WR-02A | |
| C7 | 10μ | 16V 3216 | CN4 | 35001WR-02A | |
| C8 | 10n | 50V 1608 K | CN5 | 35001WR-02A | |
| C9 | 10μ | 16V 3216 | Transformer (DIP) | | |
| C10 | 220p | 50V 1608 K | TX1 | | EFD2126 |
| C11 | 10n | 50V 1608 K | TX2 | | EFD2126 |
| C12 | 1μ | 50V 2012 K | | | |

Physical Dimensions




Figure 58. 20-SOIC Package


Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings:
<http://www.fairchildsemi.com/packaging/>



TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

- | | | | |
|---|---|---|---|
| 2Cool™ | FlashWriter SM | PDP SPM™ | The Power Franchise [®] |
| AccuPower™ | FPST™ | Power-SPM™ | The Right Technology for Your Success™ |
| Auto-SPM™ | F-PFST™ | PowerTrench [®] | the power franchise |
| AX-CAP™ | FRFET [®] | PowerXS™ | TinyBoost™ |
| BitSiC [®] | Global Power Resource SM | Programmable Active Droop™ | TinyBuck™ |
| Build it Now™ | Green FPS™ | QFET [®] | TinyCalc™ |
| CorePLUS™ | Green FPS™ e-Series™ | QST™ | TinyLogic [®] |
| CorePOWER™ | Gmax™ | Quiet Series™ | TINYOPTO™ |
| CROSSVOLT™ | GTO™ | RapidConfigure™ | TinyPower™ |
| CTL™ | IntelliMAX™ |  | TinyPWM™ |
| Current Transfer Logic™ | ISOPLANAR™ | Saving our world, 1mW/kW at a time™ | TinyWire™ |
| DEUXPEED [®] | MegaBuck™ | SignalWise™ | TranSiC [®] |
| Dual Cool™ | MICROCOUPLER™ | SmartMax™ | TriFault Detect™ |
| EcoSPARK [®] | MicroFET™ | SMART START™ | TRUECURRENT ^{®*} |
| EfficientMax™ | MicroPak™ | SPM [®] | μSerDes™ |
| ESBC™ | MicroPak2™ | STEALTH™ |  |
|  | MillerDrive™ | SuperFET [®] | UHC [®] |
| Fairchild [®] | MotionMax™ | SuperSOT™-3 | Ultra FRFET™ |
| Fairchild Semiconductor [®] | Motion-SPM™ | SuperSOT™-6 | UniFET™ |
| FACT Quiet Series™ | mWSaver™ | SuperSOT™-8 | VCX™ |
| FACT [®] | OptoHiT™ | SupreMOS [®] | VisualMax™ |
| FAST [®] | OPTOLOGIC [®] | SyncFET™ | XS™ |
| FastvCore™ | OPTOPLANAR [®] | Sync-Lock™ | |
| FETBench™ |  |  | |

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

| Datasheet Identification | Product Status | Definition |
|--------------------------|-----------------------|---|
| Advance Information | Formative / In Design | Datasheet contains the design specifications for product development. Specifications may change in any manner without notice. |
| Preliminary | First Production | Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design. |
| No Identification Needed | Full Production | Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design. |
| Obsolete | Not In Production | Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only. |

Rev. I55