

EMF450 Multi-Field EMF Meter



• Multi-Field measurements: Magnetic Field, Electric

• Adjustable screen brightness (low, medium, high)

Field, and Radio Frequency (RF) Strength

• Magnetic Field Triple Axis Sensor (X, Y, Z)

• 2.4" (240 x 320 pixels) color TFT display

Convenient 3-in-1 EMF meter simultaneously measures and displays Magnetic Field, Electric Field, and Radio Frequency Strength. Ergonomic pocket-sized design with an easy-to-navigate menu. Large vivid color TFT display shows digital readings, bargraphs, and trending graph.

- Industrial devices

- Base stations

- Mobile/cell phones

Applications:

- Home appliances
- Power lines,Electrical appliances
 - ncal appliances
- Store up to 20 RF historical records
- Data Hold and Auto Power Off with disable feature

EXTECH

1435

EME45

IN A A

Hold Menu

Multi-Field EMF Meter

- Five languages: English, Traditional/Simplified Chinese, Japanese, Spanish
- Complete with 3 AAA batteries

Specifications	Range	Max Resolution	Basic Accuracy
Magnetic Fields (50/60Hz)	20/200/2000mG	0.02/0.1/1mG	±(15%+100 digit)
	2/20/200µT	0.02/0.1/1µT	
Electric Fields (50/60Hz)	50V/m to 2000V/m		±(7% + 50dgt)
RF Strength (50MHz to 3.5GHz)	0.02uW/m² to 554.6mW/m²	0.02µW/m²	
	0.02uW/cm ² to 55.4uW/cm ²	0.002µW/cm ²	
	36.1mV/m to14.46V/m	0.2mV/m	
	0.02mA/m to 38.35mA/m	0.2µA/m	
	-51dB to 16dBm	2dB	±2dB at 2.45GHz
Dimensions/ Weight	4.5 x 2.4 x 0.8" (115 x 60 x 21mm)/ 4.2oz (120g)		
Bargraph	Magnetic Fields	RF Strength	Electric Field
Green	0 to 10.00mG	0 to 0.99mW/m ²	0 to 500V/m
		0 to 0.59V/m	
Yellow	10.01 to 100mG	1 to 9.99mW/m ²	501 to 1000V/m
		0.6 to 1.9V/m	
Red	101 to 2000mG	>10mW/m²	>1001V/m
		>2V/m	

Ordering

Features

• Audible alarm

EMF450 Multi-Field EMF Meter

www.extech.com