# PCP1103

# **Bipolar Transistor** -30V, -1.5A, Low VCE(sat) PNP Single PCP



· DC / DC converters, relay drivers, lamp drivers, motor drivers, IGBT gate drivers

# Features

• Adoption of MBIT process

- Large current capacity
- High speed switching
- Low collector to emitter saturation voltageHigh allowable power dissipation
- Halogen free compliance

# **Specifications**

#### Absolute Maximum Ratings at Ta=25°C

Symbol	Conditions	Ratings	Unit
VCBO		-30	V
VCEO		-30	V
VEBO		-5	V
IC		-1.5	A
ICP		-5	А
	VCBO VCEO VEBO IC	VCBO   VCEO   VEBO   IC	VCBO -30   VCEO -30   VEBO -5   IC -1.5

Continued on next page.

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

# Package Dimensions

unit : mm (typ) 7007B-004

December, 2013



### Product & Package Information

- Package
- JEITA, JEDEC : SC-62, SOT-89, TO-243

: PCP

• Minimum Packing Quantity : 1,000 pcs./reel

#### Packing Type: TD

 $\bigcirc$ 





Marking

### **Electrical Connection**

TD





#### Continued from preceding page.

Parameter	Symbol	Conditions	Ratings	Unit
Base Current	IB		-300	mA
Collector Dissipation	PC	When mounted on ceramic substrate (450mm <sup>2</sup> ×0.8mm)	1.3	W
		Tc=25°C	3.5	W
Junction Temperature	Tj		150	°C
Storage Temperature	Tstg		-55 to +150	°C

#### Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Unit
	Symbol		min	typ	max	UIII
Collector Cutoff Current	ICBO	V <sub>CB</sub> = -30V, I <sub>E</sub> =0A			-0.1	μΑ
Emitter Cutoff Current	IEBO	V <sub>EB</sub> = -4V, I <sub>C</sub> =0A			-0.1	μΑ
DC Current Gain	hFE	$V_{CE} = -2V, I_{C} = -100 \text{mA}$	200		560	
Gain-Bandwidth Product	fT	VCE= -10V, IC= -300mA		450		MHz
Output Capacitance	Cob	V <sub>CB</sub> = -10V, f=1MHz		9		рF
Collector to Emitter Saturation Voltage	V <sub>CE</sub> (sat)	I <sub>C</sub> = -0.75A, I <sub>B</sub> = -15mA		-250	-375	mV
Base to Emitter Saturation Voltage	V <sub>BE</sub> (sat)	I <sub>C</sub> = -0.75A, I <sub>B</sub> = -15mA		-0.85	-1.2	V
Collector to Base Breakdown Voltage	V(BR)CBO	IC= -10μΑ, IE=0A	-30			V
Collector to Emitter Breakdown Voltage	V(BR)CEO	IC= −1mA, RBE=∞	-30			V
Emitter to Base Breakdown Voltage	V(BR)EBO	I <sub>E</sub> = -10μΑ, I <sub>C</sub> =0Α	-5			V
Turn-On Time	ton			35		ns
Storage Time	tstg	See specified Test Circuit.		115		ns
Fall Time	tf			30		ns

### Switching Time Test Circuit



#### **Ordering Information**

Device	Package	Shipping	memo
PCP1103-TD-H	PCP	1,000pcs./reel	Pb Free and Halogem Free







## Outline Drawing PCP1103-TD-H



#### Land Pattern Example



ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typical" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal