

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Device circuit breaker boards for eight thermomagnetic (CB TM1...) or electronic (CB E1... NO) circuit breakers with group remote signaling, central supply, connection for relay contacts, and potential distribution for up to four loads per channel.

Why buy this product

- ☑ Reduced installation time thanks to multi-channel device Circuit Breakers Board (4/8/12 channels)
- ☑ Space savings of up to 35% thanks to compact design
- ☑ Fuse protection of up to 12 A per channel provides best possible protection for connected loads
- Up to 4 loads can be protected simultaneously with the additional terminal points
- Integrated group remote signaling ensures that you are always kept informed
- High current carrying capacity of the board supports supply of up to 60 A

Maximum overcurrent protection over long cable paths thanks to device circuit breakers with SFB characteristic curve or electronic device circuit breakers

RoHS

Key Commercial Data

Packing unit	1 STK
GTIN	4 046356 934459
GTIN	4046356934459

Technical data

Dimensions

Height	127.8 mm
Width	170 mm
Depth	70.8 mm

Ambient conditions

Ambient temperature (operation)	-30 °C 60 °C (at 48 A, see derating)
Ambient temperature (storage/transport)	-30 °C 80 °C
Humidity test	96h, 93% RH, 40 °C
Degree of protection	IP20 (Terminal blocks and fuse holders)



Technical data

Ambient conditions

	IP00 (PCB)
General	

Flammability rating according to UL 94	V0
Mounting type	DIN rail: 35 mm
Number of positions	8
Overvoltage category_GRP	Ш
Protection class	III
Degree of pollution	2
Туре	DIN rail module, two-section, divisible

Electrical data

Rated voltage main circuit	24 V DC
Rated current main circuit	60 A DC (total)
	12 A DC (per channel)
Rated voltage remote indication circuit	24 V DC
Rated current remote indication circuit	0.5 A DC
Rated surge voltage	0.5 kV
Short circuit stability	600 A (conditional according to DIN EN 50178)
Power dissipation	4.9 W (without circuit breaker)
Insertion/withdrawal cycles	50

Connection data

Connection name	Supply X21
Connection method	Push-in connection
Stripping length	18 mm
Conductor cross section solid	0.75 mm ² 16 mm ²
Conductor cross section AWG	20 4
Conductor cross section, flexible, with ferrule, with plastic sleeve	0.75 mm ² 10 mm ²
Conductor cross section flexible, with ferrule without plastic sleeve	0.75 mm ² 16 mm ²
Connection name	Outputs X1 X8
Connection method	Push-in connection
Stripping length	10 mm
Conductor cross section solid	0.2 mm ² 4 mm ²
Conductor cross section AWG	24 12
Conductor cross section, flexible, with ferrule, with plastic sleeve	0.25 mm ² 1.5 mm ²
Conductor cross section flexible, with ferrule without plastic sleeve	0.25 mm ² 2.5 mm ²
Connection name	Remote signaling X31
Connection method	Push-in connection
Stripping length	10 mm
Conductor cross section solid	0.2 mm ² 4 mm ²
Conductor cross section AWG	24 12



Technical data

Connection data

Conductor cross section, flexible, with ferrule, with plastic sleeve	0.25 mm ² 1.5 mm ²
Conductor cross section flexible, with ferrule without plastic sleeve	0.25 mm ² 2.5 mm ²
Standards and Regulations	
Standards/specifications	DIN EN 50178 1997
	DIN EN 61000-6-2:2005
	DIN EN 61000-6-3:2007+A1:2011
	DIN EN 60068-2-6

REACh SVHC Lead 7439-92-1

Drawings





Circuit diagram





Application drawing



Approvals

Approvals

Approvals
EAC
Ex Approvals
Approval details

EAC EAC RU C-DE.A*30.B01561

08/18/2018 Page 4 / 5



Phoenix Contact 2018 © - all rights reserved http://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstr. 8 32825 Blomberg Germany Tel. +49 5235 300 Fax +49 5235 3 41200 http://www.phoenixcontact.com