

# POWER TRANSFORMER **Chassis Mount: International Series**

# VPL10-500

#### Electrical Specifications (@25C)

- 1. Maximum Power: 5.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz 3. Output Voltage Series<sup>1</sup>: 10.0V CT@ 0.500A, Parallel<sup>2</sup>: 5.0V @ 1.00A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.



#### Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

## **Agency Files:**

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV Certificate No.: R72103639, EN60950, Information Technology





Dimensions:				Units: In inche	
Α	В	С	D	Е	F
1.437	2.375	1.437	2.00	8.00	0.187

Weight: 0.4 lbs.

### Connections<sup>3</sup>:

Input: Series - BLK to BLU, Jumper WHT to BRN


Parallel - BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series - RED to GRY, Jumper YEL to VIO

Parallel - RED to GRY, Jumper RED to VIO and YEL to GRY

RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.





<sup>&</sup>lt;sup>2</sup> Inherently limited. No fusing required. Class 2.

<sup>&</sup>lt;sup>3</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.









**SCHEMATIC** 

Publish Date: December 4, 2013